



MACHINEDRUM SOUND PACK

01: DEEP RHYTHMS

You may use the content of this Sound Pack on a 100% royalty-free basis in your original music compositions (which include, but is not limited to, soundtracks of such as films, video productions, radio/TV programs or commercials, computer games and multimedia presentations, library music). You may broadcast and/or distribute your own music compositions or audio projects that were created using the content of the Sound Pack. However, the content of the Sound Pack may not be commercially or otherwise distributed on a standalone basis, hosted and used in non Elektron devices, nor may it be repackaged in whole or in part as audio samples, sound effects or music beds.

SOUND PACK CONTENT

- 4 Snapshots each containing 1 song and 4 patterns
- 4 Sample banks
- 93 ROM samples

Some Sample banks may contain loops adjusted to a specific BPM. To hear the demo patterns as they were intended we recommend switching to the Machinedrum SONG mode before listening to them.

RECOMMENDED REQUIREMENTS FOR THE SOUND PACK

This Sound Pack is specifically made for +Drive equipped MKII models of the Machinedrum UW. Some Sample banks may need more sample memory than MKI units support and all patterns consist of 64 steps. We strongly recommend you have Machinedrum OS 1.62 or higher installed before transferring the Sound Pack content to the Machinedrum. To make the transfer process as smooth as possible, C6 v 1.4 or higher should be used.

TRANSFERRING THE SOUND PACK CONTENT TO YOUR MACHINEDRUM

Download and install the free program C6. It is found in the Support and Downloads section of the Elektron website. Connect the computer you are sending the files from to your Machinedrum by using a MIDI interface. We recommend using our TM-1 USB MIDI interface. Open the Configure menu in C6 and make sure the ports of the MIDI interface are activated.

DETAILED TRANSFER INSTRUCTIONS

1. After extracting the content of the Sound Pack zip-file, open the Snapshot/Sample bank folder you want to transfer.
2. Locate the .c6 file. Drag and drop it to the C6 window. All sample and data syx files of the folder will be added to the C6 list. At the top of the list the song/pattern/kit syx file will be placed.
3. Open up the Machinedrum GLOBAL menu by pressing [FUNCTION] + [PATTERN/SONG]. Choose any slot and press [ENTER/YES].
4. Open the FILE → SNAPSHOTS menu. Select an empty Snapshot assigned to an empty Sample bank. As no Snapshot names will be automatically assigned during the data transfer we recommend you to rename the Snapshot, preferably to the same name as the folder containing the Snapshot/Sample bank. This goes for the Sample bank as well.
5. Exit the SNAPSHOTS menu and enter the SAMPLE MGR. Select RECV and the ORG method of receipt. Press [ENTER/YES]. The Machinedrum will now wait for the samples to be sent. Note that the sample syx files contain position markers. If you want to place the samples in other positions, do not use the ORG method. This, however, is not recommended.

Continued on next page →

WE ARE ELEKTRON, WE MAKE MAGICAL MUSIC INSTRUMENTS

Elektron Music Machines, Sockerbruket 9, 414 51, Gothenburg, Sweden

Phone: +46 31 743 744 0 • Fax: +46 31 743 744 9 • SALES@ELEKTRON.SE • WWW.ELEKTRON.SE

6. In C6, select all syx files except the first one containing the song/pattern/kit data. The easiest way to do this is to select the second to first file in the list, then press the shift key on your computer keyboard while clicking on the last SYX file. If you are using a TM-1 interface, active the Turbo Mode. Press the Send button in C6. Exit the SAMPLE MGR once the sample transfer is complete.
7. Open FILE → SYSEX REC. Select the ORG option and press [ENTER/YES]. The Machinedrum will now wait for the song/pattern/kit data to be sent.
8. In C6, select the first file in the list. Press the Send button.
9. After the transfer is complete, enter the FILE → SNAPSHOTS menu and save the Snapshot.
10. Repeat steps 1 to 9 for the rest of the Sound Pack folders.

SIMPLIFIED TRANSFER INSTRUCTIONS

1. After extracting the content of the Sound Pack zip-file, open the Snapshot/Sample bank folder you want to transfer.
2. Locate the .c6 file. Drag and drop it to the C6 window. All sample and data SYX files of the folder will be added to the C6 list.
3. Open the SNAPSHOT QUICK MODE menu by long pressing [FUNCTION] + [PATTERN/SONG]. Select an empty Snapshot assigned to an empty Sample bank. Exit the menu.
4. In C6, select all SYX files. The easiest way to do this is to select first file in the list, then press the shift key on your computer keyboard while clicking on the last file. If you are using a TM-1 interface, active the Turbo Mode. Press the Send button in C6.
5. After the transfer is complete, enter the GLOBAL → FILE → SNAPSHOTS menu and save the Snapshot. As no Snapshot names will be automatically assigned during the data transfer we recommend you to rename the Snapshot, preferably to the same name as the folder containing the Snapshot/Sample bank. This goes for the Sample bank as well.
6. Repeat steps 1 to 5 for the rest of the Sound Pack folders.

CREDITS

Samples recorded by Filip Leyman.

Editing and programming by Daniel Troberg and Filip Leyman.

WE ARE ELEKTRON, WE MAKE MAGICAL MUSIC INSTRUMENTS

Elektron Music Machines, Sockerbruket 9, 414 51, Gothenburg, Sweden

Phone: +46 31 743 744 0 • Fax: +46 31 743 744 9 • SALES@ELEKTRON.SE • WWW.ELEKTRON.SE

LIST OF SOUND PACK 01 SAMPLES AS THEY APPEAR IN THE SAMPLE MGR

DEEP RHYTHMS	DUB1	DUB2	REGGAE1	REGGAE2
01	BD01	BD01	BD01	BD01
02	SD01	SD01	BD02	SD01
03	SD02	SD02	SD01	SD02
04	SD03	SD03	SD02	TOM1
05	SD04	SD04	SD03	TOM2
06	SD05	HH01	SD04	RS01
07	SD06	HH02	TOM1	RS02
08	TOM1	OH01	TOM2	CB01
09	TOM2	RC01	HH01	CB02
10	RS01	DJM1	HH02	CB03
11	RS02	DJM2	HH03	HH01
12	RS03	DJM3	OH01	HH02
13	HH01	DJM4	OH02	OH01
14	HH02	DJM5	TMB1	OH02
15	OH01	GR01	TMB2	RC01
16	CC01	GR02	TMB3	FX01
17	CLV1	GR03	TMB4	FX02
18	CBS1	FX01	TMB5	FX03
19	CBS2	FX02	GR01	FX04
20	FX01	FX03	GR02	FX05
21	FX02		GR03	
22	FX03		GR04	
23			CBS1	
24			CBS2	
25		OLP1		BLP1
26		PLP1		MLP1
27		BLP1		MLP2
28				MLP3
29				
30				
31				
32				
33				
34				
35				
36				
37				
38				
39				
40				
41				
42				
43				
44				
45				
46				
47				
48				

WE ARE ELEKTRON, WE MAKE MAGICAL MUSIC INSTRUMENTS

Elektron Music Machines, Sockerbruket 9, 414 51, Gothenburg, Sweden

Phone: +46 31 743 744 0 • Fax: +46 31 743 744 9 • SALES@ELEKTRON.SE • WWW.ELEKTRON.SE