

---

## IMMORTAL WAVES SOUND PACK

This sound pack, made exclusively for the Monomachine, contains a generous helping of user waveforms of a very distinct nature. They will be instantly familiar to all who have experienced the cutting sounds of the classic analog synthesizer Minimoog Model D. All waveforms are assembled by Radek Rudnicki. The Patterns and Kits are crafted by Elektron. Please note that this Sound Pack will only work on MKII +DRIVE versions.

Basic knowledge of Monomachine functionality is required. If you need to brush up on navigation or interaction with your instrument, please consult the **User's Manual**, available for download free of charge on the Elektron webpage, Support & Downloads Section.

The package includes 64 waveforms, 16 kits and 16 patterns. The patterns will give you an inkling of what sounds and tunes you will be able to produce once the waveforms are loaded into your machine.

### TRANSFERRING THE WAVEFORMS TO A NEW SNAPSHOT

1. Save your current Snapshot. Select the FILE row in the GLOBAL EDIT menu. Then select SNAPSHOTS and press **[ENTER/YES]**. In the MODE column, select SAVE and press **[ENTER/YES]**.
2. Load a new empty Snapshot. Select the FILE row in the GLOBAL EDIT menu. Select SNAPSHOTS and press **[ENTER/YES]**. Choose LOAD in the MODE column and select an empty position in the list.
3. Connect your Monomachine MIDI IN to a computer using a standard MIDI connector and a MIDI interface. Connect via the Elektron TM-1 in order to achieve Turbomidi (up to 10x) transfer speeds.
4. Initiate a new DIGIBANK on the Monomachine. Select the FILE row in the GLOBAL EDIT menu. Then select DIGIBANKS and press **[ENTER/YES]**. First, select SWITCH in the MODE column and choose an empty position for your new bank. Then, select RENAME and give the bank a suitable name (IMMORTAL, for example, but you can give it any name you want) using the **[FUNCTION] + [ARROW]** keys.
5. Prepare the Monomachine to receive the waveforms. Access the DIGIPRO MGR in the GLOBAL menu. Choose RECEIVE and then press **[RIGHT]** arrow key to move to the POS NAME column. Choose ORG and press **[ENTER/YES]**. The display on the Monomachine will show "WAITING..."
6. On your computer, open the c6 utility software (make sure you have the latest version, available on the Elektron webpage, Support & Downloads section). In the c6 configuration menu, select Elektron Monomachine for both MIDI In and MIDI Out. Also, make sure you tick the boxes: Use SDS Handshake, Use Extended SDS and Send SPS-1UW Name. This will allow the transferred data to be shown with descriptive names, once received. Close the configuration window by clicking the OK button.
7. Open the Immortal Waves Sound Pack folder on your computer. Drag the waveform files and drop them on the c6 main window. Select all files. Then click the DigiPro button, located below right on the c6 main window. Finally, click the Send button. A counter on your Monomachine display will show how many and to which position the waveforms have been received.
8. When all waveforms have been transferred, press **[EXIT/NO]**. The Monomachine screen will show "WRITING WAVEFORMS". The transfer is complete. The waveforms will be stored starting from position 1 in the active Digibank.
9. Transfer the kits and patterns. On the Monomachine, Select FILE in the GLOBAL menu. Then select SYSEX RECV using the **[ARROW]** keys and press **[ENTER/YES]**. In the MODE column, select ORIG and press **[ENTER/YES]**. The Monomachine is now ready to receive data, and "WAITING..." will be shown on the screen. On your computer, drag the Immortal Waves (Patterns and Kits) syx file to the c6 main window. Select the file, then click Send. After a short while, the Patterns and Kits will have been transferred.
10. Save your new Snapshot. Select FILE in the GLOBAL EDIT menu. Then, select SNAPSHOTS and press **[ENTER/YES]**. Select SAVE in the MODE column and press **[ENTER/YES]**. Give the Snapshot a proper name, such as IMMORTAL, using the **[FUNCTION] + [ARROW]** keys.

### PLAY BACK THE SOUND PACK PATTERNS

1. The 16 demo patterns are located in Bank A. Make sure bank group A-D is active (toggle using the **[BANK GROUP]** key). Then select a pattern by pressing **[BANK A/E] + [TRIG]** 1-16.
2. Listen to the selected pattern by pressing **[PLAY]**.

The Sounds of the Monomachine sound packs remain the property of its manufacturer (Collectively, "Licensor") and are licensed to you as the original end-user ("Licensee"), for use subject to the provisions below. All rights not expressly granted herein are reserved exclusively by Licensor.

The Sounds in a category of 'Sound pack':

1. The Licensee may use the Sounds in combination with other sounds in music productions (which include soundtracks of such as films, video productions, radio/TV programs or commercials, computer games and multimedia presentations, library music), public performances, and other reasonable musical purposes within musical compositions.
2. The Licensee may modify the Sounds and may use the Sounds for commercial purposes as part of a musical composition with other sounds.
3. The Licensee MAY NOT use the Sounds in isolation as sound effects (i.e. a sequence of musical events) or within any competitive products that are sold or relicensed to multiple third parties. In these scenarios the Licensee must arrange an extension with Elektron Music Machines.
4. A right to use the sounds is granted only to the Licensee and is NOT transferable. This license expressly forbids resale, relicensing or other distribution of the Sounds, either as they exist or any modification thereof. You cannot sell, loan, rent, lease, assign, upload to or download from any server, or transfer all or any of the enclosed sounds to another user, or for use in any competitive product.
5. Licensor will not be responsible if the sounds do not fit the particular purpose of the Licensee.